

1 TITLE OF THE INVENTION

2 **Method and System for Connecting a Mobile Communication Unit**
3 **to a Personal Computer**

4 BACKGROUND OF THE INVENTION

5 Field of the Invention

6 The present invention relates generally to personal computers, and
7 more specifically to a method and a system for connecting a mobile unit to a
8 computer.

9 Description of the Related Prior Art

10 It is known to use a connection device for coupling a cellular mobile
11 telephone to a personal computer to provide data communication via a
12 mobile network. A known connection device as disclosed in Japanese Patent
13 Publication 97-162960 is comprised of an AC-DC converter battery charger
14 for charging the battery of the mobile unit with energy obtained from a
15 commercial AC outlet. However, due to the use of AC-DC converter battery
16 charger, a commercial AC outlet must be available at a suitable location and a
17 power supply code must be attached to the connection device for receiving
18 AC energy from the power outlet. Another connection device disclosed in
19 Japanese Patent Publication 98-285254 includes a first power connector for
20 exclusively for use in charging the battery of a mobile unit and a second
21 power connector exclusively for use in operating the mobile unit. These
22 power connectors are provided separately from a data connector that is used
23 to transport data between the mobile unit and a personal computer. While
24 the use of two power connectors allows the mobile unit to proceed
25 communication with the mobile network while its battery is being charged, a

SECRET

3

4

8

7

8

9

20

21

2

3

4

5

1 the established connection according to a command signal entered to the
2 computer.

3 According to a third aspect, the present invention provides a
4 connection device for establishing connections between a computer and a
5 mobile communication unit having a rechargeable battery. The connection
6 device comprises a connector having a recess for holding the mobile
7 communication unit and a plurality of connector ports, and an interface card
8 connected through the connector ports to the internal circuitry of the mobile
9 communication unit and connected through a serial port to the internal
10 circuitry of the computer. The interface card includes power supply circuitry
11 for supplying power from a power source of the computer to the
12 rechargeable battery of the mobile communication unit, switching circuitry
13 for selectively establishing a connection between the internal circuitry of the
14 computer and the internal circuitry of the mobile communication unit
15 through the connector ports, and control circuitry for controlling the mobile
16 communication unit through the connection according to a command signal
17 entered to the computer.

18 BRIEF DESCRIPTION OF THE DRAWINGS

19 The present invention will be described in detail further with reference
20 to the following drawings, in which:

21 Fig. 1 is a perspective view of a notebook computer and a connector
22 for coupling a mobile unit to the computer according to the present
23 invention;

24 Fig. 2 is a block diagram of a personal computer and an interface card
25 according to the present invention;

1 Fig. 3 is a block diagram of a mobile unit according to the present
2 invention;

3 Fig. 4 is a perspective view of a computer screen on which a simulated
4 image of the mobile unit is displayed; and

5 Fig. 5 is a perspective view of a connector in which the interface card
6 of the present invention is installed.

7 DETAILED DESCRIPTION

8 Referring to Fig. 1, there is shown a personal computer and a
9 connector 4 for coupling a mobile communication unit 5 to the computer 1
10 and for operating the mobile unit 5 from the computer 1 according to the
11 present invention. For the purpose of disclosure, the computer 1 is shown
12 and described as a notebook computer having a keyboard 2 incorporated as
13 an integral part of the computer. A headset 3 is connected to the computer 1
14 to be used by the computer user. The connector 4 has a recess in which the
15 mobile unit 5 is placed in an upright position. Connector 4 establishes
16 connections between its internal circuitry and an interface card 25 inserted in
17 a slot formed in the housing of computer 1.

18 In Fig. 2, the notebook computer 1 includes a control circuit 10 to
19 which the keyboard 2 of the computer 1 is connected, a voice processor 11, a
20 packet processor 12 and a fax transceiver 13, all of which are connected to a
21 USB (universal serial bus) interface 18. Voice processor 11 has a first analog
22 input port for receiving a voice signal from the microphone 3A and converts
23 it to a digital voice signal at a rate much lower than 64 kbps and a first digital
24 output port from which the digital voice signal is delivered. In addition, the
25 voice processor 11 has a second digital input port for receiving a lower-than-

00000107-020001

1 64 kbps digital voice signal from the mobile unit 5 and converts it to an
2 analog voice signal and a second analog output port from which the analog
3 voice signal is delivered to the speaker 3B.

4 In response to command signals from the keyboard 2, the controller 10
5 produces a number of control signals including an on/off control signal for
6 providing a power-on-off control over the mobile unit 5, a voice recognition
7 control signal for controlling the voice recognition circuit of the mobile unit, a
8 mode control signal for operating the mobile unit in one of voice, packet and
9 facsimile modes, and a dialing signal for placing a call in a manner as will be
10 described. Further provided is a voice-to-text converter 14 connected to the
11 microphone 3A for converting the voice input into character data, which is
12 displayed via a video processor 16 on the screen of a display unit 17. A voice-
13 input message for an electronic mail can be produced in this way and
14 transmitted in packets from the packet processor 12.

15 A graphics data source 15 is provided to respond to an input from the
16 keyboard 2 to produce a simulated image of the mobile unit on the computer
17 screen in order that the user is given an impression that he is directly
18 operating the mobile's keypad from the keyboard 2. All internal circuits of
19 the computer 1 are supplied with a DC voltage from a rechargeable battery
20 19, which also supplies its power to the mobile unit via the USB interface 18.
21 Keyboard 2 supplies a command to the controller 10 for enabling the voice-to-
22 text converter 14 and the graphics data source 15.

23 Interface card 25 is connected to the connector 4 via industry-
24 standardized connector ports designated "a" through "j" and a grounded
25 port not shown. Interface card 25 includes a USB interface 21 which is

21 The voice recognition control signal from the controller 10 is repeated
22 by the phone controller 24 to the mobile unit 5 in order to receive a response
23 signal (text data) indicating a phone number corresponding to an uttered
24 subscriber name into the microphone 3A. A phone attachment/detachment
25 signal is received from the connector 4, the signal being applied to the USB

[illegible]

1 interface 21 for activating the controller 10 when the mobile unit 5 is held in
2 upright position on the connector 4.

3 In Fig. 3, the mobile unit 5 includes a controller 30 for providing
4 interactive communication with the phone controller 24 by exchanging serial
5 command and serial response signals. A voice processor 31 similar to the
6 voice processor 11 is provided. A packet processor 32 and a fax transceiver
7 33 are provided for communication with the packet processor 12 and fax
8 transceiver 13. A phone attachment sensor 34 is provided in the connector 4
9 to supply a phone attachment signal through connector port "i" to the
10 interface card 25 in order to activate the controller 10 when the mobile unit is
11 placed on the connector 4. When the mobile unit is removed from the
12 connector 4, a phone detachment signal will be sent to the computer 1.

13 The mobile unit 5 has a rechargeable battery 35 that is charged with
14 the DC voltage supplied from the rechargeable battery 19 of the computer.
15 All internal circuits of the mobile unit 5 except for power saving circuitry are
16 energized by the battery 35 via a power switch 36 which is controlled by an
17 ON/Off control signal from the controller 30.

18 Switches 40 and 49 are provided to selectively establish paths or
19 logical connections under control of the controller 30, as indicated by the
20 dotted lines.

21 A wireless interface 48 is connected to the voice processor 31, packet
22 processor 32 and fax transceiver 33 as well as to the memory 43 to receive a
23 dialed phone number. Wireless interface 48 establishes a wireless
24 communication link to the mobile network and initiates a call according to
25 the phone number supplied from the memory 43. During an exclusively

00002487, 030804

10 11 12 13 14 15 16 17 18 19 20 21 22 23 24 25 26 27 28 29 30 31 32 33 34 35 36 37 38 39 40 41 42 43 44 45 46 47 48 49 50 51 52 53 54 55 56 57 58 59 60 61 62 63 64 65 66 67 68 69 70 71 72 73 74 75 76 77 78 79 80 81 82 83 84 85 86 87 88 89 90 91 92 93 94 95 96 97 98 99 100 101 102 103 104 105 106 107 108 109 110 111 112 113 114 115 116 117 118 119 120 121 122 123 124 125 126 127 128 129 130 131 132 133 134 135 136 137 138 139 140 141 142 143 144 145 146 147 148 149 150 151 152 153 154 155 156 157 158 159 160 161 162 163 164 165 166 167 168 169 170 171 172 173 174 175 176 177 178 179 180 181 182 183 184 185 186 187 188 189 190 191 192 193 194 195 196 197 198 199 200 201 202 203 204 205 206 207 208 209 210 211 212 213 214 215 216 217 218 219 220 221 222 223 224 225 226 227 228 229 230 231 232 233 234 235 236 237 238 239 240 241 242 243 244 245 246 247 248 249 250 251 252 253 254 255 256 257 258 259 260 261 262 263 264 265 266 267 268 269 270 271 272 273 274 275 276 277 278 279 280 281 282 283 284 285 286 287 288 289 290 291 292 293 294 295 296 297 298 299 300 301 302 303 304 305 306 307 308 309 310 311 312 313 314 315 316 317 318 319 320 321 322 323 324 325 326 327 328 329 330 331 332 333 334 335 336 337 338 339 340 341 342 343 344 345 346 347 348 349 350 351 352 353 354 355 356 357 358 359 360 361 362 363 364 365 366 367 368 369 370 371 372 373 374 375 376 377 378 379 380 381 382 383 384 385 386 387 388 389 390 391 392 393 394 395 396 397 398 399 400 401 402 403 404 405 406 407 408 409 410 411 412 413 414 415 416 417 418 419 420 421 422 423 424 425 426 427 428 429 430 431 432 433 434 435 436 437 438 439 440 441 442 443 444 445 446 447 448 449 450 451 452 453 454 455 456 457 458 459 460 461 462 463 464 465 466 467 468 469 470 471 472 473 474 475 476 477 478 479 480 481 482 483 484 485 486 487 488 489 490 491 492 493 494 495 496 497 498 499 500 501 502 503 504 505 506 507 508 509 510 511 512 513 514 515 516 517 518 519 520 521 522 523 524 525 526 527 528 529 530 531 532 533 534 535 536 537 538 539 540 541 542 543 544 545 546 547 548 549 550 551 552 553 554 555 556 557 558 559 560 561 562 563 564 565 566 567 568 569 570 571 572 573 574 575 576 577 578 579 580 581 582 583 584 585 586 587 588 589 590 591 592 593 594 595 596 597 598 599 600 601 602 603 604 605 606 607 608 609 610 611 612 613 614 615 616 617 618 619 620 621 622 623 624 625 626 627 628 629 630 631 632 633 634 635 636 637 638 639 640 641 642 643 644 645 646 647 648 649 650 651 652 653 654 655 656 657 658 659 660 661 662 663 664 665 666 667 668 669 670 671 672 673 674 675 676 677 678 679 680 681 682 683 684 685 686 687 688 689 690 691 692 693 694 695 696 697 698 699 700 701 702 703 704 705 706 707 708 709 710 711 712 713 714 715 716 717 718 719 720 721 722 723 724 725 726 727 728 729 730 731 732 733 734 735 736 737 738 739 740 741 742 743 744 745 746 747 748 749 750 751 752 753 754 755 756 757 758 759 760 761 762 763 764 765 766 767 768 769 770 771 772 773 774 775 776 777 778 779 780 781 782 783 784 785 786 787 788 789 790 791 792 793 794 795 796 797 798 799 800 801 802 803 804 805 806 807 808 809 810 811 812 813 814 815 816 817 818 819 820 821 822 823 824 825 826 827 828 829 830 831 832 833 834 835 836 837 838 839 840 841 842 843 844 845 846 847 848 849 850 851 852 853 854 855 856 857 858 859 860 861 862 863 864 865 866 867 868 869 870 871 872 873 874 875 876 877 878 879 880 881 882 883 884 885 886 887 888 889 890 891 892 893 894 895 896 897 898 899 900 901 902 903 904 905 906 907 908 909 910 911 912 913 914 915 916 917 918 919 920 921 922 923 924 925 926 927 928 929 930 931 932 933 934 935 936 937 938 939 940 941 942 943 944 945 946 947 948 949 950 951 952 953 954 955 956 957 958 959 960 961 962 963 964 965 966 967 968 969 970 971 972 973 974 975 976 977 978 979 980 981 982 983 984 985 986 987 988 989 990 991 992 993 994 995 996 997 998 999 1000 1001 1002 1003 1004 1005 1006 1007 1008 1009 1010 1011 1012 1013 1014 1015 1016 1017 1018 1019 1020 1021 1022 1023 1024 1025 1026 1027 1028 1029 1030 1031 1032 1033 1034 1035 1036 1037 1038 1039 1040 1041 1042 1043 1044

Speed dialing memory 43 is connected to a video processor 44, through which phone numbers read out of the memory 43 can be displayed on a phone display panel 45. When the mobile unit is not attached to the computer 1, the phone display 45 provides a display of a phone number supplied from the speed dialing memory 43 and textual data generated by a keypad 46.

25 The following is a description of the operation of the computer 1 when

1 the mobile unit 5 is attached to the computer by way of the connector 4.

2 When the mobile unit 5 is held in position on the recess of connector 4,
3 the phone attachment sensor 34 senses its presence and produces a phone
4 attachment signal, which is sent through connector port "i" to the controller
5 10 via USB interfaces 21 and 18. Note that all signals communicated between
6 the USB interfaces 18 and 21 over the USB port 20 are in the form of packets.
7 Controller 10 is enabled in response to the phone attachment signal so that it
8 is ready for accepting command signals from the keyboard 2.

9 In response to a keyboard operation by the user, the controller 10
10 produces a turn-on signal, which is sent through the phone controller 24 to
11 the controller 30 of the mobile unit and turns on the switch 36. Mobile unit 5
12 is activated to establish a wireless control channel to the mobile network. As
13 long as the voltage of rechargeable battery 19 is higher than a specified level,
14 the voltage sensor 22 will activate the battery charger 23 for charging the
15 mobile's rechargeable battery 35 through connector port "j".

16 If the user desires to place a phone call using the mobile's speed
17 dialing memory 43 and voice recognition unit 41 in a manner similar to that
18 during the exclusive mobile mode, he sets the controller 10 through the
19 keyboard 2 to produce a voice recognition control signal and a telephony
20 (voice) mode signal, which are applied to the phone controller 24. Controller
21 24 repeats the signals to the controller 30 via connector port "a". Controller
22 30 operates the switches 40 and 49 to establish paths 55 and 56 for connecting
23 the digital output of voice processor 11 which is applied through connector
24 port "c" to the digital input of voice processor 31 and a path 57 (in switch 40)
25 for connecting the analog output of the voice processor 31 to the voice

1 recognition unit 41. Simultaneously, the voice processor 11 is enabled by the
2 controller 10.

3 The user then utters the name of a called party into the microphone
4 3A. The voice signal from the microphone 3A is applied to the voice
5 processor 11, where the voice input is converted to a low-rate digital speech
6 signal and sent through connector port "c" to the voice processor 31. An
7 analog voice output is generated by the voice processor 31 and applied
8 through the path 57 to the voice recognition unit 41 and converted to text
9 data, which is used by the memory 43 to make a search for a corresponding
10 phone number. This phone number is sent from the controller 30 through
11 connector port "b" to the phone controller 24, where it is delivered through a
12 control bus 70 to the video processor 16 and displayed on the screen of the
13 computer display 17. On the other hand, the same phone number is supplied
14 on line 71 (Fig. 3) to the wireless interface 48 for initiating a call. When a call
15 is established, the controller 30 controls the switches 40 and 49 so that paths
16 58, 59 and 60 are established for connecting the digital output of voice
17 processor 11 (which is received through connector port "c") to the digital
18 input of the wireless interface 48 and connecting the digital output of wireless
19 interface 48 to the digital input of voice processor 11 via connector port "d".

20 When the user activates the graphics data source 15 through keyboard
21 2, an image 72 of the mobile unit 5 is displayed on the computer screen as
22 shown in Fig. 4.

23 By operating a numeral key on the keyboard 2, the corresponding key
24 is lit on the simulated mobile's image. At the same time, the entered numeral
25 data is sent from the controller 10 to the phone controller 24 which repeats

1 - the signal to the mobile controller 30. By repeating this process, the user can
2 enter the address information of a called party and the controller 30 receives
3 this address information and sends it to the wireless interface 48 through line
4 71, which then establishes a communication link through the cellular mobile
5 network.

6 When the user enables the voice-to-text converter 14 through the
7 keyboard 2, a voice message can be entered through the microphone 3A to
8 the voice-to-text converter 14, from which a text-converted data is supplied to
9 the video processor 16 and displayed on the computer screen. An electronic
10 mail can be formulated with such text data and transmitted to the mobile's
11 controller 30 through USB interfaces 18, 21 and phone controller 24 to the
12 connector port "a". In this way, the user is relieved of having to manipulate
13 the mobile's small keys which are usually need to be operated repeatedly for
14 entering a desired character.

15 Phone controller 24 allows phone numbers entered through the
16 keyboard 2 to be transmitted as serial data through connector port "a" and
17 stored into the speed dialing memory 43 of the mobile unit and allows e-mail
18 messages to be displayed on the computer screen, instead of on the small-
19 sized mobile's screen. Further, the phone controller 24 allows all operating
20 status information of the mobile unit 5 to be received through serial data port
21 "b" and put on display on the computer screen.

22 The user can specify from the keyboard 2 to the controller 10 as to
23 which one of packet and facsimile modes is used to initiate a call. In response
24 to such a keyboard input, the controller 10 produces a mode select signal
25 (packet/fax) and enables one of the packet processor 12 or fax transceiver 13,

00000107 000001

1 - which is repeated by the phone controller 24 to the mobile's controller 30 via
2 connector port "a". Controller 30, in response, establishes a two-way path in
3 the switch 40 between one of the packet processor 12 and fax transceiver 13
4 and a corresponding one of the packet processor 32 and fax transceiver 33.

5 If the call is in a telephony mode, the voice input to the microphone 3A
6 is applied to the voice processor 11, where the signal is converted according
7 to a predetermined coding algorithm to a lower-than-64-kbps digital voice
8 signal and passed through the switches 40 and 49 to the wireless interface 48.
9 This signal is translated to an uplink signal and transmitted to the mobile
10 network. Digital voice signal from the network is carried on a downlink
11 signal and received by the wireless interface 48, the digital voice signal being
12 supplied via the switches 49 and 40 and connector ports "c" and "d" to the
13 voice processor 11 where it is processed back to the original analog signal and
14 applied to the speaker 3B.

15 If the mode select signal from the controller 10 indicates that the user
16 wishes to send packets, the packet processor 12 is enabled by the controller 10
17 to send packets to the mobile's packet processor 32 via connector port "e" for
18 transmission to the mobile network. Packets from the network are first
19 processed by the mobile's packet processor 32 and sent to the computer's
20 packet processor 12 to be displayed on the computer screen. In a similar
21 manner, the fax transceivers 13 and 33 are used for exchanging fax signals
22 with remote stations.

23 It is seen that the user is relieved from the need to find a commercial
24 AC outlet for charging the mobile unit 5 and from the need to use a power
25 code for coupling the mobile unit to the AC outlet. Another advantage of the

Fig. 5 shows an alternative embodiment of the present invention. In this embodiment, the interface card 25 is located within the housing of the connector 4. In this case, the USB port 20 takes the form of a four-wire cable 80 extending from the connector 4 to a USB port 81 of the computer 1.